



Buy







TPS7A87

ZHCSF74A - MARCH 2016-REVISED JULY 2016

TPS7A87 双路 500mA 低噪声 (3.8 µVRMS) LDO 稳压器

特性 1

- 两个独立的 LDO 通道
- 低输出噪声: 3.8µV_{RMS} (10Hz-100kHz)
- 低压降: 电流为 0.5A 时_{最大} 100mV
- 宽输入电压范围: 1.4V 至 6.5V
- 宽输出电压范围: 0.8V 至 5.2V
- 高电源纹波抑制:
 - 直流时为 75dB
 - 100kHz 时为 40dB
 - 1MHz 时为 40dB
- 整个线路、负载和温度范围内的精度达 1.0%
- 出色的负载瞬态响应
- 可调节的启动浪涌控制
- 可选软启动充电电流
- 独立开漏电源正常 (PGx) 输出
- 与 10µF 或更大的陶瓷输出电容一起工作时保持稳 定
- 4mm × 4mm 20 引脚超薄型四方扁平无引线 (WQFN) 封装

2 应用

- 高速模拟电路:
 - 压控振荡器 (VCO)、模数转换器 (ADC)、数模 转换器 (DAC) 以及低压差分信令 (LVDS)
- 成像: 互补金属氧化物半导体 (CMOS) 传感器,视 频专用集成电路 (ASIC)
- 测试和测量
- 仪器仪表和医疗
- 专业音频



典型应用电路

3 说明

Tools &

Software

TPS7A87 是一款双路低噪声 (3.8µV_{RMS}) 低压降 (LDO) 稳压器,每通道具有 500mA 的拉电流能力,其 最高压降仅为100mV。

TPS7A87 提供两个独立的 LDO, 极具灵活性, 解决方 案尺寸要比两个单通道 LDO 小 30% 左右。每个输出 可通过外部电阻在 0.8V 至 5.2 V 范围内进行调节。 TPS7A87 的宽输入电压范围支持其在 1.4V 至 6.5V 范 围内的电压下工作。

TPS7A87 的输出电压精度(整个线路、负载和温度范 围内)达1%,并且可通过软启动功能减少浪涌电流, 因此非常适合为敏感类模拟低压器件 [例如,压控振荡 器 (VCO)、模数转换器 (ADC)、数模转换器 (DAC)、 互补金属氧化物半导体 (CMOS) 传感器和视频特定用 途集成电路 (ASIC)] 供电。

TPS7A87旨在为噪声敏感类组件供电,广泛适用于仪 器仪表、医疗、视频、专业音频、测试和测量以及高速 通信等应用。此器件具有 3.8 µV_{RMS} 的超低输出噪声 和宽带电源抑制比 (PSRR) (1MHz 时为 40dB),最 大限度减少了相位噪声和时钟抖动。这些 功能 最大限 度提升了计时器件、ADC 和 DAC 的性能。

器件信息(1)

器件型号	封装	封装尺寸(标称值)			
TPS7A87	WQFN (20)	4.00mm x 4.00mm			

(1) 如需了解所有可用封装,请见数据表末尾的可订购产品附录。



Copyright © 2016, Texas Instruments Incorporated



An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

Copyright © 2016, Texas Instruments Incorporated

目录

8

9

11

11.5

1	特性	
2	应用	
3	说明	1
4	修订	历史记录 2
5	Pin	Configuration and Functions 3
6	Spe	cifications 4
	6.1	Absolute Maximum Ratings 4
	6.2	ESD Ratings 4
	6.3	Recommended Operating Conditions 4
	6.4	Thermal Information 4
	6.5	Electrical Characteristics 5
	6.6	Typical Characteristics 6
7	Deta	ailed Description 13
	7.1	Overview 13
	7.2	Functional Block Diagram 13
	7.3	Feature Description 14
	7.4	Device Functional Modes 17

view	13
tional Block Diagram	13
ure Description	14
ce Functional Modes	17

4 修订历史记录

注: 之前版本的页码可能与当前版本有所不同。

Changes from Original (March 2016) to Revision A	Page
• 已发布为"量产数据"	1



Application and Implementation 18 8.1 Application Information...... 18 8.2 Typical Application 32

10.1 Layout Guidelines 34 10.2 Layout Example 35 器件和文档支持 36

11.3 接收文档更新通知 36

11.6 静电放电警告...... 37

www.ti.com.cn



5 Pin Configuration and Functions



Pin Functions

PIN			
NAME	NO.	I/O	DESCRIPTION
EN1	20		Enable pin for each channel. These pins turn the regulator on and off. If $V_{ENx}^{(1)} \ge V_{IH(ENx)}$, then the regulator is enabled.
EN2	6		If $V_{ENx} \leq V_{IL(ENx)}$, then the regulator is disabled. The ENx pin must be connected to INx if the enable function is not used.
FB1	16		Feedback pin connected to the error amplifier. Although not required, a 10-nF feed-forward capacitor from FBx to OUTx
FB2	10	I	(as close to the device as possible) is recommended to maximize ac performance. The use of a feed-forward capacitor can disrupt PGx (power good) functionality. See the <i>Feed-Forward Capacitor (C_{FFx})</i> and <i>Setting the Output Voltage (Adjustable Operation)</i> sections for more details.
GND	3, 13	_	Ground pin. These pins must be connected to ground, the thermal pad, and each other with a low-impedance connection.
IN1	1, 2	I	Input supply pin for LDO 1. A 10 μ F or greater input capacitor is required. Place the input capacitor as close to the input as possible.
IN2	4, 5	I	Input supply pin for LDO 2. A 10 μ F or greater input capacitor is required. Place the input capacitor as close to the input as possible.
NR/SS1	19		Noise-reduction and soft-start pin for each channel. Connecting an external capacitor between this pin and ground
NR/SS2	7	_	reduces reference voltage noise and also enables the soft-start function. Although not required, a 10 nF or larger capacitor is recommended to be connected from NR/SSx to GND (as close to the pin as possible) to maximize ac performance. See the <i>Noise-Reduction and Soft-Start Capacitor</i> ($C_{NR/SSx}$) section for more details.
OUT1	14, 15	0	Regulated output for LDO 1. A 10- μ F or larger ceramic capacitor (5 μ F or greater of effective capacitance) from OUTx to ground is required for stability and must be placed as close to the output as possible. Minimize the impedance from the OUT1 pin to the load. See the <i>Input and Output Capacitor</i> (C_{INx} and C_{OUTx}) section for more details.
OUT2	11, 12	0	Regulated output for LDO 2. A 10- μ F or larger ceramic capacitor (5 μ F or greater of effective capacitance) from OUTx to ground is required for stability and must be placed as close to the output as possible. Minimize the impedance from the OUT2 pin to the load. See the <i>Input and Output Capacitor</i> (C_{INx} and C_{OUTx}) section for more details.
PG1	17	_	Open-drain power-good indicator pins for the LDO 1 and LDO 2 output voltages. A 10-k Ω to 100-k Ω external pullup
PG2	9	0	resistor is required. These pins can be left floating or connected to GND if not used. The use of a feed-forward capacitor can disrupt power-good functionality. See the <i>Feed-Forward Capacitor (C_{FFX})</i> section for more details.
SS_CTRL1	18	1	Soft-start control pin for each channel. Connect these pins either to GND or INx to allow normal or fast charging of the
SS_CTRL2	8		NR/SSx capacitor. If a C _{NR/SSx} capacitor is not used, SS_CTRLx must be connected to GND to avoid output overshoot.
Thermal pad		—	Connect the thermal pad to a large-area ground plane. The thermal pad is internally connected to GND.

(1) Lowercase x indicates that the specification under consideration applies to both channel 1 and channel 2, one channel at a time.



6 Specifications

6.1 Absolute Maximum Ratings

over operating junction temperature range and all voltages with respect to GND (unless otherwise noted)⁽¹⁾

		MIN	MAX	UNIT	
	INx, PGx, ENx ⁽²⁾	-0.3	7.0		
	INx, PGx, ENx (5% duty cycle, pulse duration = 200 µs)	-0.3	7.5		
Voltage	OUTx	-0.3	$V_{INx} + 0.3^{(3)}$	V	
	SS_CTRLx	-0.3	$V_{INx} + 0.3^{(3)}$		
	NR/SSx, FBx ⁽²⁾	-0.3	3.6		
Current	OUTx ⁽²⁾	Interna	ally limited	А	
Current	PGx (sink current into device) ⁽²⁾		5	mA	
Tomporatura	Operating junction, T _J	-55	150	ŝ	
Temperature	Storage, T _{stg}	-55	150	C	

(1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(2) Lowercase x indicates that the specification under consideration applies to both channel 1 and channel 2, one channel at a time.

(3) The absolute maximum rating is V_{INx} + 0.3 V or 7.0 V, whichever is smaller.

6.2 ESD Ratings

			VALUE	UNIT
V _(ESD) Electrostatic discharg	Electrostatio discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001 ⁽¹⁾	±2000	V
	Electrostatic discharge	Charged device model (CDM), per JEDEC specification JESD22-C101 ⁽²⁾	±500	V

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.

(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating junction temperature range (unless otherwise noted)

		MIN	MAX	UNIT
V _{INx}	Input supply voltage range	1.4	6.5	V
V _{OUTx}	Output voltage range	0.8 – 1%	5.2 + 1%	V
I _{OUTx}	Output current	0	500	mA
C _{INx}	Input capacitor, each input	10		μF
C _{OUTx}	Output capacitor	10		μF
C _{NR/SSx}	Noise-reduction capacitor		1	μF
R _{PGx}	Power-good pullup resistance	10	100	kΩ
TJ	Junction temperature range	-40	125	°C

6.4 Thermal Information

		TPS7A87		
	THERMAL METRIC ⁽¹⁾	RTJ (WQFN)	UNIT	
		20 PINS		
$R_{ hetaJA}$	Junction-to-ambient thermal resistance	33	°C/W	
R _{0JC(top)}	Junction-to-case (top) thermal resistance	26.8	°C/W	
$R_{\theta JB}$	Junction-to-board thermal resistance	8.0	°C/W	
ΨJT	Junction-to-top characterization parameter	0.3	°C/W	
Ψјв	Junction-to-board characterization parameter	8.0	°C/W	
R _{0JC(bot)}	Junction-to-case (bottom) thermal resistance	2.4	°C/W	

 For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report (SPRA953).

6.5 Electrical Characteristics

over operating temperature range ($T_J = -40^{\circ}C$ to +125°C), $V_{INx} = 1.4$ V or $V_{OUTx(TARGET)} + 0.2$ V (whichever is greater), $V_{OUTx(TARGET)} = 0.8$ V, $I_{OUTx} = 50$ mA, $V_{ENx} = 1.4$ V, $C_{OUTx} = 10$ µF, $C_{NR/SSx} = 0$ nF, $C_{FFx} = 0$ nF, SS_CTRLx = GND, PGx pin pulled up to V_{INx} with 100 k Ω , and for each channel (unless otherwise noted); typical values are at $T_J = 25^{\circ}C$

	PARAMETER	TEST CONDITIONS	MIN	ТҮР	MAX	UNIT
V _{INx} ⁽¹⁾	Input supply voltage range		1.4		6.5	V
V _{REF}	Reference voltage			0.8		V
V _{UVLOx}	Input supply UVLOx	V _{INx} rising		1.31	1.39	V
V _{UVLOx(HYS)}	V _{UVLOx} hysteresis	V _{INx} falling hysteresis		290		mV
V _{OUTx}	Output voltage range		0.8 – 1%		5.2 + 1%	V
	V _{OUTx} accuracy ⁽²⁾	$0.8 \text{ V} \le \text{V}_{\text{OUTx}} \le 5.2 \text{ V}, 5 \text{ mA} \le \text{I}_{\text{OUTx}} \le 0.5 \text{ A}$	-1.0%		1.0%	
$\Delta V_{OUTx(\Delta VINx)}$	Line regulation	$I_{OUTx} = 5 \text{ mA}, 1.4 \text{ V} \le V_{INx} \le 6.5 \text{ V}$		0.003		%/V
$\Delta V_{OUTx(\Delta IOUTx)}$	Load regulation	$5 \text{ mA} \le I_{\text{OUTx}} \le 0.5 \text{ A}$		0.03		%/A
V _{DO}	Dropout voltage	$1.4 \text{ V} \le \text{V}_{\text{INx}} \le 5.3 \text{ V}$ $\text{I}_{\text{OUTx}} = 0.5 \text{ A}, \text{V}_{\text{FBx}} = 0.8 \text{ V} - 3\%$			100	mV
I _{LIM}	Output current limit	V_{OUTx} forced at 0.9 × $V_{OUTx(TARGET)}$,	0.8	1.1	1.5	А
	GND pin current	Both channels enabled, per channel, $V_{INx} = 6.5 \text{ V}, I_{OUTx} = 5 \text{ mA}$		2.1	3.5	mA
GND	·	Both channels enabled, per channel, $V_{INx} = 1.4 V$, $I_{OUTx} = 0.5 A$			4	
I _{SDN}	Shutdown GND pin current	Both channels shutdown, per channel, PGx = (open), V_{INx} = 6.5 V, V_{ENx} = 0.4 V		0.1	15	μΑ
I _{ENx}	ENx pin current	$V_{INx} = 6.5 \text{ V}, \ 0 \text{ V} \leq V_{ENx} \leq 6.5 \text{ V}$	-0.2		0.2	μΑ
V _{IL(ENx)}	ENx pin low-level input voltage (device disabled)		0		0.4	V
V _{IH(ENx)}	ENx pin high-level input voltage (device enabled)		1.1		6.5	V
I _{SS_CTRLx}	SS_CTRLx pin current	$V_{INx} = 6.5 \text{ V}, 0 \text{ V} \le V_{SS_CTRLx} \le 6.5 \text{ V}$	-0.2		0.2	μΑ
V _{IT(PGx)}	PGx pin threshold	For PGx transitioning low with falling V _{OUTx} , expressed as a percentage of V _{OUTx(TARGET)}	82%	88.9%	93%	
V _{hys(PGx)}	PGx pin hysteresis	For PGx transitioning high with rising V_{OUTx} , expressed as a percentage of $V_{OUTx(TARGET)}$		1%		
V _{OL(PGx)}	PGx pin low-level output voltage	$V_{OUTx} < V_{IT(PGx)}$, $I_{PGx} = -1$ mA (current into device)			0.4	V
I _{lkg(PGx)}	PGx pin leakage current	$V_{OUTx} > V_{IT(PGx)}, V_{PGx} = 6.5 V$			1	μA
I _{NR/SSx}	NR/SSx pin charging current	$V_{NR/SSx} = GND, 1.4 V \le V_{INx} \le 6.5 V,$ $V_{SS_CTRLx} = GND$	4.0	6.2	9.0	μA
		$V_{NR/SSx} = GND, 1.4 V \le V_{INx} \le 6.5 V, V_{SS_CTRLx} = V_{INx}$	65	100	150	
I _{FBx}	FBx pin leakage current	$V_{\text{INx}} = 6.5 \text{ V}, V_{\text{FBx}} = 0.8 \text{V}$	-100		100	nA
PSRR	Power-supply rejection ratio	$ \begin{array}{l} f=500 \text{ kHz}, \text{ V}_{\text{INx}}=3.8 \text{ V}, \text{ V}_{\text{OUTx}}=3.3 \text{ V}, \\ \text{I}_{\text{OUTx}}=250 \text{ mA}, \text{ C}_{\text{NR/SSx}}=10 \text{ nF}, \text{ C}_{\text{FFx}}=10 \text{ nF} \end{array} $		40		dB
V _n	Output noise voltage	$\begin{split} BW &= 10 \text{ Hz to } 100 \text{ kHz}, \text{V}_{\text{INx}} = 1.8 \text{ V}, \text{V}_{\text{OUTx}} = 0.8 \text{ V}, \\ \text{I}_{\text{OUTx}} &= 0.5 \text{ A}, \text{C}_{\text{NR/SSx}} = 1 \text{\mu}\text{F}, \text{C}_{\text{FFx}} = 100 \text{ n}\text{F} \end{split}$		3.8		μV_{RMS}
	Noise spectral density			11		nV/√Hz
R _{diss}	Output active discharge resistance	V _{ENx} = GND		250		Ω
т.	Thermal shutdown temporature	Shutdown, temperature increasing		160		۰C
' sdx		Reset, temperature decreasing	140		C	

(1) Lowercase x indicates that the specification under consideration applies to both channel 1 and channel 2.

(2) When the device is connected to external feedback resistors at the FBx pins, external resistor tolerances are not included.

TPS7A87 ZHCSF74A – MARCH 2016 – REVISED JULY 2016



www.ti.com.cn

6.6 Typical Characteristics





Typical Characteristics (接下页)





Typical Characteristics (接下页)





Typical Characteristics (接下页)





Typical Characteristics (接下页)





Typical Characteristics (接下页)





Typical Characteristics (接下页)





7 Detailed Description

7.1 Overview

The TPS7A87 is a monolithic, dual-channel, low-dropout (LDO) regulator, and each channel is low-noise, high-PSRR, and capable of sourcing a 500-mA load with only 100 mV of maximum dropout. These features make the device a robust solution to solve many challenging problems in generating a clean, accurate power supply.

The various features for each of the TPS7A87 fully independent LDOs simplify using the device in a variety of applications. As detailed in the *Functional Block Diagram* section, these features are organized into three categories, as shown in $\frac{1}{8}$ 1.

Easturas

农 1. Features				
VOLTAGE REGULATION	SYSTEM START-UP	INTERNAL PROTECTION		
High accuracy	Programmable soft-start	Foldback current limit		
Low-noise, high-PSRR output	Sequencing controls			
Fast transient response	Power-good output	memai shuldown		

7.2 Functional Block Diagram





7.3 Feature Description

7.3.1 Voltage Regulation Features

7.3.1.1 DC Regulation

An LDO functions as a class-B amplifier in which the input signal is the internal reference voltage (V_{REF}), as shown in \mathbb{R} 41. V_{REF} is designed to have a very low-bandwidth at the input to the error amplifier through the use of a low-pass filter ($V_{NR/SSx}$).

As such, the reference can be considered as a pure dc input signal. The low output impedance of an LDO comes from the combination of the output capacitor and pass element. The pass element also presents a high input impedance to the source voltage when operating as a current source. A positive LDO can only source current because of the class-B architecture.

This device achieves a maximum of 1% output voltage accuracy primarily because of the high-precision bandgap voltage (V_{BG}) that creates V_{REF} . The low dropout voltage (V_{DO}) reduces the thermal power dissipation required by the device to regulate the output voltage at a given current level, thereby improving system efficiency. Combined, these features help make this device a good approximation of an ideal voltage source.

This device replaces two stand-alone power-supplies, and also provides load-to-load isolation. The LDOs can also be put in series (cascaded) to achieve even higher PSRR by connecting the output of one channel to the input of the other channel.



NOTE: $V_{OUTx} = V_{REF} \times (1 + R_{1x} / R_{2x}).$

图 41. Simplified Regulation Circuit

7.3.1.2 AC and Transient Response

Each LDO responds quickly to a transient (large-signal response) on the input supply (line transient) or the output current (load transient) resulting from the LDO high-input impedance and low output-impedance across frequency. This same capability also means that each LDO has a high power-supply rejection-ratio (PSRR) and, when coupled with a low internal noise-floor (V_n), the LDO approximates an ideal power supply in ac (small-signal) and large-signal conditions.

The performance and internal layout of the device minimizes the coupling of noise from one channel to the other channel (crosstalk). Good printed circuit board (PCB) layout minimizes the crosstalk.

The choice of external component values optimizes the small- and large-signal response. The NR/SSx capacitor ($C_{NR/SSx}$) and feed-forward capacitor (C_{FFx}) easily reduce the device noise floor and improve PSRR; see the *Optimizing Noise and PSRR* section for more information on optimizing the noise and PSRR performance.

7.3.2 System Start-Up Features

In many different applications, the power-supply output must turn-on within a specific window of time to either ensure proper operation of the load or to minimize the loading on the input supply or other sequencing requirements. Each LDO start-up is well-controlled and user-adjustable, solving the demanding requirements faced by many power-supply design engineers in a simple fashion.



PGx = 0

PGx = 0

www.ti.com.cn

Feature Description (接下页)

7.3.2.1 Programmable Soft-Start (NR/SSx)

Soft-start directly controls the output start-up time and indirectly controls the output current during start-up (inrush current).

The external capacitor at the NR/SSx pin ($C_{NR/SSx}$) sets the output start-up time by setting the rise time of the internal reference ($V_{NR/SSx}$), as shown in \mathbb{Z} 42. SS_CTRLx provides additional control over the rise time of the internal reference by enabling control over the charging current ($I_{NR/SSx}$) for $C_{NR/SSx}$. The voltage at the SS_CTRLx pin ($V_{SS \ CTRLx}$) must be connected to ground (GND) or V_{INx} .

Note that if $C_{NR/SSx} = 0$ nF and the SS_CTRLx pin is connected to V_{INx} , then the output voltage overshoots during start-up.



图 42. Simplified Soft-Start Circuit

7.3.2.2 Sequencing

Controlling when a single power supply turns on can be difficult in a power distribution network (PDN) because of the high power levels inherent in a PDN, and the variations between all of the supplies. Control of each channel turn-on and turn-off time is set by the specific channel enable circuit (ENx) and undervoltage lockout circuit (UVLOx), as shown in \mathbb{R} 43 and $\frac{1}{5}$ 2.





A 2. Ocquencing runctionality runce					
OLTAGE	ENABLE STATUS	LDO STATUS	ACTIVE DISCHARGE	POWER-GOOD	
	ENx = 1	On	Off	$PGx = 1$ when $V_{OUTx} \ge V_{IT(PGx)}$	

表 2. Sequencing Functionality Table

On

On⁽¹⁾

(1) The active discharge remains on as long as V_{INx} provides enough headroom for the discharge circuit to function.

Off

Off

ENx = 0

ENx = don't care

7.3.2.2.1 Enable (ENx)

V_{INx} ≥ V_{UVLOx}

 $V_{INx} < V_{UVLOx} - V_{HYS}$

INPUT V

The enable signal (V_{ENx}) is an active-high digital control that enables the LDO when the enable voltage is past the rising threshold ($V_{ENx} \ge V_{IH(ENx)}$) and disables the LDO when the enable voltage is below the falling threshold ($V_{ENx} \le V_{IL(ENx)}$). The exact enable threshold is between $V_{IH(ENx)}$ and $V_{IL(ENx)}$ because ENx is a digital control. In applications that do not use the enable control, connect ENx to V_{INx} .

7.3.2.2.2 Undervoltage Lockout (UVLOx) Control

The UVLOx circuit responds quickly to glitches on V_{INx} and attempts to disable the output of the device if either of these rails collapse.

As a result of the fast response time of the input supply UVLOx circuit, fast and short line transients well below the input supply UVLOx falling threshold (brownouts) can cause momentary glitches during the edges of the transient. These glitches are typical in most LDOs and, in most applications, the brownouts required for these glitches do not result from the local input capacitance; see the *Undervoltage Lockout (UVLOx) Control* section for more details.

7.3.2.2.3 Active Discharge

When either ENx or UVLOx is low, the device connects a resistor of several hundred ohms from V_{OUTx} to GND, discharging the output capacitance.

Do not rely on the active discharge circuit for discharging large output capacitors when the input voltage drops below the targeted output voltage. Current flows from the output to the input (reverse current) when $V_{OUTx} > V_{INx}$, which can cause damage to the device (when $V_{OUTx} > V_{INx} + 0.3$ V); see the *Reverse Current Protection* section for more details.

7.3.2.3 Power-Good Output (PGx)

The PGx signal provides an easy solution to meet demanding sequencing requirements because PGx signals when the output nears its nominal value. PGx can be used to signal other devices in a system when the output voltage is near, at, or above the set output voltage ($V_{OUTx(Target)}$). A simplified schematic is shown in \mathbb{E} 44.

The PGx signal is an open-drain digital output that requires a pullup resistor to a voltage source and is active high. The power-good circuit sets the PGx pin into a high-impedance state to indicate that the power is good.

Using a large feed-forward capacitor (C_{FFx}) delays the output voltage and, because the power-good circuit monitors the FBx pin, the PGx signal can indicate a false positive. A simple solution to this scenario is to use an external voltage detector device, such as the TPS3780; see the *Feed-Forward Capacitor* (C_{FFx}) section for more information.



图 44. Simplified PGx Circuit



7.3.3 Internal Protection Features

In many applications, fault events can occur that damage devices in the system. Short-circuits and excessive heat are the most common fault events for power supplies. The TPS7A87 implements circuitry for each LDO to protect the device and its load during these events. Continuously operating in these fault conditions or above a junction temperature of 125°C is not recommended because the long-term reliability of the device is reduced.

7.3.3.1 Foldback Current Limit (I_{CLx})

7.3.3.2 Thermal Protection (T_{sdx})

The thermal shutdown circuit protects the LDO against excessive heat in the system, either resulting from current limit or high ambient temperature. Each channel features its own independent thermal shutdown circuit.

The output of the LDO turns off when the LDO temperature (junction temperature, T_J) exceeds the rising thermal shutdown temperature (T_{sdx}). The output turns on again after T_J decreases below the falling thermal shutdown temperature (T_{sdx}).

A high power dissipation across the device, combined with a high ambient temperature (T_A), can cause T_J to be greater than or equal to T_{sdx} , triggering the thermal shutdown and causing the output to fall to 0 V. The LDO can cycle on and off when thermal shutdown is reached under these conditions.

7.4 Device Functional Modes

表 3 provides a quick comparison between the regulation and disabled operation.

	PARAMETER				
OPERATING MODE	V _{INx}	ENx	Ι _{ουτx}	Tj	
Regulation ⁽¹⁾	$V_{INx} > V_{OUTx(nom)} + V_{DO}$	$V_{ENx} > V_{IH(ENx)}$	I _{OUTx} < I _{CLx}	T _J < T _{sd}	
Disabled ⁽²⁾	V _{INx} < V _{UVLOx}	V _{ENx} < V _{IL(ENx)}	_	$T_J > T_{sd}$	

表 3. Device Functional Modes Comparison

(1) All table conditions must be met.

(2) The device is disabled when any condition is met.

7.4.1 Regulation

The device regulates the output to the targeted output voltage when all the conditions in $\frac{1}{5}$ are met.

7.4.2 Disabled

When disabled, the pass device is turned off, the internal circuits are shutdown, and the output voltage is actively discharged to ground by an internal resistor from the output to ground.



Application and Implementation 8

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

Successfully implementing an LDO in an application depends on the application requirements. This section discusses key device features and how to best implement them to achieve a reliable design.

8.1.1 External Component Selection

8.1.1.1 Setting the Output Voltage (Adjustable Operation)

Each LDO resistor feedback network sets the output voltage, as shown in 8 45, with an output voltage range of 0.8 V to 5.2 V.



Copyright © 2016, Texas Instruments Incorporated

图 45. Adjustable Operation

公式 1 relates the values R_{1x} and R_{2x} to V_{OUTx(Target)} and V_{FBx}. 公式 1 is a rearranged version of 公式 2, simplifying the feedback resistor calculation. The current through the feedback network must be equal to or greater than 5 μ A for optimum noise performance and accuracy, as shown in $\Delta \pm 3$.

$V_{OUTx} = V_{FBx} \times (1 + R_{1x} / R_{2x})$	(1)
$R_{1x} = (V_{OUTx} / V_{FBx} - 1) \times R_{2x}$	(2)
$R_{2x} < V_{REF} / 5 \mu A$	(3)

The input bias current into the error amplifier (feedback pin current, I_{FBx}) and tighter tolerance resistors must be taken into account for optimizing the output voltage accuracy.



Application Information (接下页)

表 4 shows the resistor combinations for several common output voltages using commercially-available, 1% tolerance resistors.

TARGETED OUTPUT	FEEDBACK RES	ISTOR VALUES ⁽¹⁾	CALCULATED OUTPUT	
VOLTAGE (V)	R _{1x} (kΩ)	R _{2x} (kΩ)	VOLTAGE (V)	
0.80	Short	Open	0.800	
0.90	1.37	11.0	0.900	
0.95	1.91	10.2	0.950	
1.00	2.55	10.2	1.000	
1.05	3.32	10.7	1.048	
1.10	3.57	9.53	1.100	
1.15	4.64	10.7	1.147	
1.20	5.49	11.0	1.199	
1.35	6.98	10.2	1.347	
1.50	9.31	10.7	1.496	
1.80	13.70	11.0	1.796	
1.90	14.70	10.7	1.899	
2.50	22.60	10.7	2.490	
2.85	27.40	10.7	2.849	
3.00	29.40	10.7	2.998	
3.30	33.20	10.7	3.282	
3.60	35.70	10.2	3.600	
4.50	44.20	9.53	4.510	
5.00	56.20	10.7	5.002	
5.20	53.60	9.76	5.193	

表 4.	Recommended	Feedback-Resistor	Values
------	-------------	--------------------------	--------

(1) R_{1x} is connected from OUTx to FBx; R_{2x} is connected from FBx to GND; see $\begin{tabular}{ll} 45. \end{tabular}$

8.1.1.2 Capacitor Recommendations

The device is designed to be stable using low equivalent series resistance (ESR) ceramic capacitors at the input and output pins. Multilayer ceramic capacitors have become the industry standard for these types of applications and are recommended, but must be used with good judgment. Ceramic capacitors that employ X7R-, X5R-, and COG-rated dielectric materials provide relatively good capacitive stability across temperature, whereas the use of Y5V-rated capacitors is discouraged because of large variations in capacitance.

Regardless of the ceramic capacitor type selected, ceramic capacitance varies with operating voltage and temperature. As a rule of thumb, derate ceramic capacitors by at least 50%. The input and output capacitors recommended herein account for an effective capacitance derating of approximately 50%, but at higher V_{INx} and V_{OUTx} conditions (that is, $V_{INx} = 5.5$ V to $V_{OUTx} = 5.0$ V) the derating can be greater than 50% and must be taken into consideration.

8.1.1.3 Input and Output Capacitor (C_{INx} and C_{OUTx})

The device is designed and characterized for operation with ceramic capacitors of 10 μ F or greater (5 μ F or greater of effective capacitance) at each input and output. Locate the input and output capacitors as near as practical to the respective input and output pins to minimize the trace inductance from the capacitor to the device.



8.1.1.4 Feed-Forward Capacitor (C_{FFx})

Although a feed-forward capacitor (C_{FFx}) from the FBx pin to the OUTx pin is not required to achieve stability, a 10-nF external C_{FFx} optimizes the transient, noise, and PSRR performance. A higher capacitance C_{FFx} can be used; however, the start-up time is longer and the power-good signal can incorrectly indicate that the output voltage is settled. The maximum recommended value is 100 nF.

To ensure proper PGx functionality, the time constant defined by $C_{NR/SSx}$ must be greater than or equal to the time constant from C_{FFx} . For a detailed description, see the *Pros and Cons of Using a Feed-Forward Capacitor with a Low Dropout Regulator* application report (SBVA042).

8.1.1.5 Noise-Reduction and Soft-Start Capacitor (C_{NR/SSx})

Although a noise-reduction and soft-start capacitor ($C_{NR/SSx}$) from the NR/SSx pin to GND is not required, $C_{NR/SSx}$ is highly recommended to control the start-up time and reduce the noise-floor of the device. The typical value used is 10 nF, and the maximum recommended value is 10 µF.

8.1.2 Start-Up

8.1.2.1 Circuit Soft-Start Control (NR/SSx)

Each output of the device features a user-adjustable, monotonic, voltage-controlled soft-start that is set with an external capacitor ($C_{NR/SSx}$). This soft-start eliminates power-up initialization problems when powering field-programmable gate arrays (FPGAs), digital signal processors (DSPs), or other processors. The controlled voltage ramp of the output also reduces peak inrush current during start-up, thus minimizing start-up transients to the input power bus.

The output voltage (V_{OUTx}) rises proportionally to $V_{NR/SSx}$ during start-up as the LDO regulates so that the feedback voltage equals the NR/SSx voltage ($V_{FBx} = V_{NR/SSx}$). As such, the time required for $V_{NR/SSx}$ to reach its nominal value determines the rise time of V_{OUTx} (start-up time).

The soft-start ramp time depends on the soft-start charging current ($I_{NR/SSx}$), the soft-start capacitance ($C_{NR/SSx}$), and the internal reference (V_{REF}). The approximate soft-start ramp time (t_{SSx}) can be calculated with $\Delta \pm 4$:

$$t_{SSx} = (V_{REF} \times C_{NR/SSx}) / I_{NR/SSx}$$

The SS_CTRLx pin for each output sets the value of the internal current source, maintaining a fast start-up time even with a large $C_{NR/SSx}$ capacitor. When the SS_CTRLx pin is connected to GND, the typical value for the $I_{NR/SSx}$ current is 6.2 µA. Connecting the SS_CTRLx pin to INx increases the typical soft-start charging current to 100 µA. The larger charging current for $I_{NR/SSx}$ is useful when smaller start-up ramp times are needed or when using larger noise-reduction capacitors.

Not using a noise-reduction capacitor on the NR/SSx pin and tying the SS_CTRLx pin to V_{INx} results in output voltage overshoot of approximately 10%. Connecting the SS_CTRLx pin to GND or using a capacitor on the NR/SSx pin minimizes the overshoot.

Values for the soft-start charging currents are provided in the *Electrical Characteristics* table.

8.1.2.1.1 In-Rush Current

In-rush current is defined as the current into the LDO at the INx pin during start-up. In-rush current then consists primarily of the sum of load current and the current used to charge the output capacitor. This current is difficult to measure because the input capacitor must be removed, which is not recommended. However, this soft-start current can be estimated by 公式 5:

$$I_{OUTx(t)} = \left[\frac{C_{OUTx} \times dV_{OUTx}(t)}{dt}\right] + \left[\frac{V_{OUTx}(t)}{R_{LOAD}}\right]$$

where:

- $V_{OUTx}(t)$ is the instantaneous output voltage of the turn-on ramp
- dV_{OUTx}(t) / dt is the slope of the V_{OUTx} ramp
- R_{LOAD} is the resistive load impedance

(5)



8.1.2.2 Undervoltage Lockout (UVLOx) Control

The UVLOx circuit ensures that the device stays disabled before its input or bias supplies reach the minimum operational voltage range, and ensures that the device properly shuts down when the input supply collapses.

图 46 and 表 5 explain the UVLOx circuit response to various input voltage events, assuming $V_{ENx} \ge V_{IH(ENx)}$.



图 46. Typical UVLOx Operation

REGION	EVENT	V _{OUTx} STATUS	COMMENT
A	Turn-on, $V_{INx} \ge V_{UVLOx}$	0	Start-up
В	Regulation	1	Regulates to target V _{OUTx}
С	Brownout, $V_{INx} \ge V_{UVLOx} - V_{HYS}$	1	The output can fall out of regulation but the device is still enabled.
D	Regulation	1	Regulates to target V _{OUTx}
E	Brownout, V _{INx} < V _{UVLOx} – V _{HYS}	0	The device is disabled and the output falls because of the load and active discharge circuit. The device is reenabled when the UVLOx rising threshold is reached by the input voltage and a normal start-up then follows.
F	Regulation	1	Regulates to target V _{OUTx}
G	Turn-off, $V_{INx} < V_{UVLOx} - V_{HYS}$	0	The output falls because of the load and active discharge circuit.

表 5. Typical UVLOx Operation Description

Similar to many other LDOs with this feature, the UVLOx circuit takes a few microseconds to fully assert. During this time, a downward line transient below approximately 0.8 V causes the UVLOx to assert for a short time; however, the UVLOx circuit does not have enough stored energy to fully discharge the internal circuits inside of the device. When the UVLOx circuit is not given enough time to fully discharge the internal nodes, the outputs are not fully disabled.

The effect of the downward line transient can be mitigated by using a larger input capacitor to increase the fall time of the input supply when operating near the minimum V_{INx} .



8.1.2.3 Power-Good (PGx) Function

The power-good circuit monitors the voltage at the feedback pin to indicate the status of the output voltage. The power-good circuit asserts whenever FBx, V_{INx} , or ENx are below their thresholds. The PGx operation versus the output voltage is shown in \mathbb{R} 47, which is described by $\frac{1}{5}$ 6.



图 47. Typical PGx Operation

REGION	EVENT	PGx STATUS	FBx VOLTAGE
А	Turn-on	0	$V_{FBx} < V_{IT(PGx)} + V_{HYS(PGx)}$
В	Regulation	Hi-Z	
С	Output voltage dip	Hi-Z	V _{FBx} ≥ V _{IT(PGx)}
D	Regulation	Hi-Z	
E	Output voltage dip	0	V _{FBx} < V _{IT(PGx)}
F	Regulation	Hi-Z	V _{FBx} ≥ V _{IT(PGx)}
G	Turn-off	0	$V_{FBx} < V_{IT(PGx)}$

表 6. Typical PGx Operation Desc	cription
---------------------------------	----------

The PGx pin is open-drain and connecting a pullup resistor to an external supply enables others devices to receive power-good as a logic signal that can be used for sequencing. Make sure that the external pullup supply voltage results in a valid logic signal for the receiving device or devices.

To ensure proper operation of the power-good circuit, the pullup resistor value must be between 10 k Ω and 100 k Ω . The lower limit of 10 k Ω results from the maximum pulldown strength of the power-good transistor, and the upper limit of 100 k Ω results from the maximum leakage current at the power-good node. If the pullup resistor is outside of this range, then the power-good signal may not read a valid digital logic level.

Using a large C_{FFx} with a small $C_{NR/SSx}$ causes the power-good signal to incorrectly indicate that the output voltage has settled during turn-on. The C_{FFx} time constant must be greater than the soft-start time constant to ensure proper operation of the PGx during start-up. For a detailed description, see the *Pros and Cons of Using a Feed-Forward Capacitor with a Low Dropout Regulator* application report (SBVA042).

The state of PGx is only valid when the device operates above the minimum supply voltage. During short brownout events and at light loads, power-good does not assert because the output voltage (therefore V_{FBx}) is sustained by the output capacitance.

8.1.3 AC and Transient Performance

LDO ac performance for a dual-channel device includes power-supply rejection ratio, channel-to-channel output isolation, output current transient response, and output noise. These metrics are primarily a function of open-loop gain, bandwidth, and phase margin that control the closed-loop input and output impedance of the LDO. The output noise is primarily a result of the reference and error amplifier noise.



8.1.3.1 Power-Supply Rejection Ratio (PSRR)

PSRR is a measure of how well the LDO control-loop rejects signals from V_{INx} to V_{OUTx} across the frequency spectrum (usually 10 Hz to 10 MHz). 公式 6 gives the PSRR calculation as a function of frequency for the input signal [$V_{INx}(f)$] and output signal [$V_{OUTx}(f)$].

$$PSRR (dB) = 20 Log_{10} \left(\frac{V_{INx}(f)}{V_{OUTx}(f)} \right)$$

(6)

Even though PSRR is a loss in signal amplitude, PSRR is shown as positive values in decibels (dB) for convenience.

A simplified diagram of PSRR versus frequency is shown in **2** 48.





图 48. Power-Supply Rejection Ratio Diagram

An LDO is often employed not only as a dc-dc regulator, but also to provide exceptionally clean power-supply voltages that exhibit ultra-low noise and ripple to sensitive system components. This usage is especially true for the TPS7A87.

The TPS7A87 features an innovative circuit to boost the PSRR between 200 kHz and 1 MHz; see 🛚 4. To achieve the maximum benefit of this PSRR boost circuit, using a capacitor with a minimum impedance in the 100-kHz to 1-MHz band is recommended.

8.1.3.2 Channel-to-Channel Output Isolation and Crosstalk

Output isolation is a measure of how well the device prevents voltage disturbances on one output from affecting the other output. This attenuation appears in load transient tests on the other output; however, to numerically quantify the rejection, the output channel isolation is expressed in decibels (dB).

Output isolation performance is a strong function of the PCB layout. See the *Layout* section on how to best optimize the isolation performance.



8.1.3.3 Output Voltage Noise

The TPS7A87 is designed for system applications where minimizing noise on the power-supply rail is critical to system performance. For example, the TPS7A87 can be used in a phase-locked loop (PLL)-based clocking circuit can be used for minimum phase noise, or in test and measurement systems where even small power-supply noise fluctuations reduce system dynamic range.

LDO noise is defined as the internally-generated intrinsic noise created by the semiconductor circuits alone. This noise is the sum of various types of noise (such as shot noise associated with current-through-pin junctions, thermal noise caused by thermal agitation of charge carriers, flicker noise, or 1/f noise and dominates at lower frequencies as a function of 1/f). 图 49 shows a simplified output voltage noise density plot versus frequency.



Frequency (Hz)

图 49. Output Voltage Noise Diagram

For further details, see the *How to Measure LDO Noise* white paper (SLYY076).

8.1.3.4 Optimizing Noise and PSRR

The ultra-low noise floor and PSRR of the device can be improved in several ways, as described in 表 7.

表 7. Effect of Various Parameters on AC Performance⁽¹⁾⁽²⁾

	NOISE			PSRR		
PARAMETER	LOW- FREQUENCY	MID- FREQUENCY	HIGH- FREQUENCY	LOW- FREQUENCY	MID- FREQUENCY	HIGH- FREQUENCY
C _{NR/SSx}	+++	No effect	No effect	+++	+	No effect
C _{FFx}	++	+++	+	++	+++	+
C _{OUTx}	No effect	+	+++	No effect	+	+++
$V_{INx} - V_{OUTx}$	+	+	+	+++	+++	++
PCB layout	++	++	+	+	+++	+++

(1) The number of +'s indicates the improvement in noise or PSRR performance by increasing the parameter value.

(2) Shaded cells indicate the easiest improvement to noise or PSRR performance.

The noise-reduction capacitor, in conjunction with the noise-reduction resistor, forms a low-pass filter (LPF) that filters out the noise from the reference before being gained up with the error amplifier, thereby minimizing the output voltage noise floor. The LPF is a single-pole filter and the cutoff frequency can be calculated with $\Delta \pm 7$. The typical value of R_{NR} is 250 k Ω . The effect of the $C_{NR/SSx}$ capacitor increases when $V_{OUTx(Target)}$ increases because the noise from the reference is gained up when the output voltage increases. For low-noise applications, a 10-nF to 10- μ F $C_{NR/SSx}$ is recommended.

 $f_{cutoff} = 1 / (2 \times \pi \times R_{NR} \times C_{NR/SSx})$

The feed-forward capacitor reduces output voltage noise by filtering out the mid-band frequency noise. The feedforward capacitor can be optimized by placing a pole-zero pair near the edge of the loop bandwidth and pushing out the loop bandwidth, thus improving mid-band PSRR.

(7)



A larger C_{OUTx} or multiple output capacitors reduces high-frequency output voltage noise and PSRR by reducing the high-frequency output impedance of the power supply.

Additionally, a higher input voltage improves the noise and PSRR because greater headroom is provided for the internal circuits. However, a high power dissipation across the die increases the output noise because of the increase in junction temperature.

Good PCB layout improves the PSRR and noise performance by providing heatsinking at low frequencies and isolating V_{OUTx} at high frequencies.

 $\frac{1}{8}$ 8 lists the output voltage noise for the 10-Hz to 100-kHz band at a 5-V output for a variety of conditions with an input voltage of 5.4 V, an R_{1x} of 12.1 kΩ, and a load current of 0.5 A. The 5-V output is chosen because this output is the worst-case condition for output voltage noise.

C _{NR/SSx} (nF)	C _{FFx} (nF)	C _{OUTx} (μF)	SS_CTRLx	OUTPUT VOLTAGE NOISE (µV _{RMS})
10	10	22	V _{INx}	10.8
1000	100	22	V _{INx}	5.6
1000	100	22	GND	5.6
1000	100	22 1000	V _{INx}	5.0

表 8. Output Noise Voltage at a 5-V Output with a 5.4-V Input

8.1.3.4.1 Charge Pump Noise

The device internal charge pump generates a minimal amount of noise.

The high-frequency components of the output voltage noise density curve are filtered out in most applications by using 10-nF to 100-nF bypass capacitors close to the load. Using a ferrite bead between the LDO output and the load input capacitors forms a pi-filter, further reducing the high-frequency noise contribution.

TEXAS INSTRUMENTS

www.ti.com.cn

8.1.3.5 Load Transient Response

ZHCSF74A-MARCH 2016-REVISED JULY 2016

TPS7A87

The load-step transient response is the output voltage response by the LDO to a step in load current, whereby output voltage regulation is maintained. There are two key transitions during a load transient response: the transition from a light to a heavy load and the transition from a heavy to a light load. The regions shown in 850 are broken down in this section and are described in 89. Regions A, E, and H are where the output voltage is in steady-state.



图 50. Load Transient Waveform

REGION	DESCRIPTION	COMMENT
А	Regulation	Regulation
В	Output current ramping	Initial voltage dip is a result of the depletion of the output capacitor charge.
С	LDO responding to transient	Recovery from the dip results from the LDO increasing its sourcing current, and leads to output voltage regulation.
D	Reaching thermal equilibrium	At high load currents the LDO takes some time to heat up. During this time the output voltage changes slightly.
E	Regulation	Regulation
F	Output current ramping	Initial voltage rise results from the LDO sourcing a large current, and leads to the output capacitor charge to increase.
G	LDO responding to transient	Recovery from the rise results from the LDO decreasing its sourcing current in combination with the load discharging the output capacitor.
Н	Regulation	Regulation

表 9. Load Transient Waveform Description



The transient response peaks ($V_{OUTx(max)}$ and $V_{OUTx(min)}$) are improved by using more output capacitance; however, doing so slows down the recovery time (W_{rise} and W_{fall}). 8 51 shows these parameters during a load transient, with a given pulse duration (PW) and current levels ($I_{OUTx(LO)}$ and $I_{OUTx(HI)}$).



图 51. Simplified Load Transient Waveform

8.1.4 DC Performance

8.1.4.1 Output Voltage Accuracy (V_{OUTx})

The device features an output voltage accuracy of 1% maximum that includes the errors introduced by the internal reference, load regulation, line regulation, and operating temperature as specified by the *Electrical Characteristics* table. Output voltage accuracy specifies minimum and maximum output voltage error, relative to the expected nominal output voltage stated as a percent.

8.1.4.2 Dropout Voltage (V_{DO})

Generally speaking, the dropout voltage often refers to the minimum voltage difference between the input and output voltage ($V_{DO} = V_{INx} - V_{OUTx}$) that is required for regulation. When V_{INx} drops below the required V_{DO} for the given load current, the device functions as a resistive switch and does not regulate output voltage. Dropout voltage is proportional to the output current because the device is operating as a resistive switch, as shown in \mathbb{R} 52.



图 52. Dropout Voltage versus Output Current

Dropout voltage is affected by the drive strength for the gate of the pass element, which is nonlinear with respect to V_{INx} on this device because of the internal charge pump. Dropout voltage increases exponentially when the input voltage nears its maximum operating voltage because the charge pump multiplies the input voltage by a factor of 4 and then is internally clamped to 8.0 V.

8.1.4.2.1 Behavior when Transitioning from Dropout into Regulation

Some applications can have transients that place the LDO into dropout, such as slower ramps on V_{INX} for startup or load transients. As with many other LDOs, the output can overshoot on recovery from these conditions.



A ramping input supply can cause an LDO to overshoot on start-up when the slew rate and voltage levels are in the right range, as shown in 853. This condition is easily avoided through either the use of an enable signal, or by increasing the soft-start time with $C_{SS/NRx}$.



图 53. Start-Up Into Dropout

8.1.5 Reverse Current Protection

As with most LDOs, this device can be damaged by excessive reverse current.

Reverse current is current that flows through the body diode on the pass element instead of the normal conducting channel. This current flow, at high enough magnitudes, degrades long-term reliability of the device resulting from risks of electromigration and excess heat being dissipated across the device. If the current flow gets high enough, a latch-up condition can be entered.

Conditions where excessive reverse current can occur are outlined in this section, all of which can exceed the absolute maximum rating of $V_{OUTx} > V_{INx} + 0.3$ V:

- If the device has a large C_{OUTx} and the input supply collapses quickly with little or no load current
- The output is biased when the input supply is not established
- The output is biased above the input supply

If excessive reverse current flow is expected in the application, then external protection must be used to protect the device. 🛚 54 shows one approach of protecting the device.



图 54. Example Circuit for Reverse Current Protection Using a Schottky Diode



8.1.6 Power Dissipation (P_D)

Circuit reliability demands that proper consideration is given to device power dissipation, location of the circuit on the printed circuit board (PCB), and correct sizing of the thermal plane. The PCB area around the regulator must be as free as possible of other heat-generating devices that cause added thermal stresses.

As a first-order approximation, power dissipation in the regulator depends on the input-to-output voltage difference and load conditions. P_D can be approximated using $\Delta \pm 8$:

$$P_{D} = (V_{OUTx} - V_{INx}) \times I_{OUTx}$$

An important note is that power dissipation can be minimized, and thus greater efficiency achieved, by proper selection of the system voltage rails. Proper selection allows the minimum input-to-output voltage differential to be obtained. The low dropout of the device allows for maximum efficiency across a wide range of output voltages.

The main heat conduction path for the device is through the thermal pad on the package. As such, the thermal pad must be soldered to a copper pad area under the device. This pad area contains an array of plated vias that conduct heat to any inner plane areas or to a bottom-side copper plane.

The maximum power dissipation determines the maximum allowable junction temperature (T_J) for the device. Power dissipation and junction temperature are most often related by the junction-to-ambient thermal resistance (θ_{JA}) of the combined PCB, device package, and the temperature of the ambient air (T_A) , according to $\Delta \pm 9$. The equation is rearranged for output current in $\Delta \pm 10$.

$$T_{J} = T_{A} + \theta_{JA} \times P_{D}$$

$$I_{OUTx} = (T_{J} - T_{A}) / [\theta_{JA} \times (V_{INx} - V_{OUTx})]$$
(10)

Unfortunately, this thermal resistance (θ_{JA}) is highly dependent on the heat-spreading capability built into the particular PCB design, and therefore varies according to the total copper area, copper weight, and location of the planes. The θ_{JA} recorded in the table is determined by the JEDEC standard, PCB, and copper-spreading area, and is only used as a relative measure of package thermal performance. Note that for a well-designed thermal layout, θ_{JA} is actually the sum of the VQFN package junction-to-case (bottom) thermal resistance (θ_{JCbot}) plus the thermal resistance contribution by the PCB copper.

8.1.6.1 Estimating Junction Temperature

The JEDEC standard now recommends the use of psi (Ψ) thermal metrics to estimate the junction temperatures of the LDO when in-circuit on a typical PCB board application. These metrics are not strictly speaking thermal resistances, but rather offer practical and relative means of estimating junction temperatures. These psi metrics are determined to be significantly independent of the copper-spreading area. The key thermal metrics (Ψ_{JT} and Ψ_{JB}) are given in the table and are used in accordance with $\Delta \vec{x}$ 11.

$$\Psi_{JT}: T_J = T_T + \Psi_{JT} \times P_D$$

$$\Psi_{JB}: T_J = T_B + \Psi_{JB} \times P_D$$

where:

- P_D is the power dissipated as explained in $\Delta \pm 8$
- T_T is the temperature at the center-top of the device package, and
- T_B is the PCB surface temperature measured 1 mm from the device package and centered on the package edge (11)

(8)



8.1.6.2 Recommended Area for Continuous Operation (RACO)

The operational area of an LDO is limited by the dropout voltage, output current, junction temperature, and input voltage. The recommended area for continuous operation for a linear regulator can be separated into the following parts, and is shown in 🛿 55:

- Limited by dropout: Dropout voltage limits the minimum differential voltage between the input and the output (V_{INx} - V_{OUTx}) at a given output current level; see the *Dropout Voltage* (V_{DO}) section for more details.
- Limited by rated output current: The rated output current limits the maximum recommended output current level. Exceeding this rating causes the device to fall out of specification.
- Limited by thermals: The shape of the slope is given by 公式 10. The slope is nonlinear because the junction temperature of the LDO is controlled by the power dissipation across the LDO; therefore, when V_{INx} V_{OUTx} increases, the output current must decrease in order to ensure that the rated junction temperature of the device is not exceeded. Exceeding this rating can cause the device to fall out of specifications and reduces long-term reliability.
- Limited by V_{INx} range: The rated input voltage range governs both the minimum and maximum of $V_{\text{INx}} V_{\text{OUTx}}$



V_{INx} – V_{OUTx} (V)

图 55. Continuous Operation Slope Region Description



图 56 to 图 61 show the recommended area of operation curves for this device on a JEDEC-standard, high-K board with a θ_{JA} = 35.4°C/W, as given in the table.





8.2 Typical Application

This section discusses the implementation of the TPS7A87 to regulate from a common input voltage to two output voltages of the same value. This application is common for when two noise-sensitive loads must have the same supply voltage but have high channel-to-channel isolation. The schematic for this application circuit is provided in 🛛 62.



Copyright © 2016, Texas Instruments Incorporated

图 62. Application Example (Single Channel)

8.2.1 Design Requirements

For the design example shown in \mathbb{Z} 62, use the parameters listed in $\frac{10}{8}$ as the input parameters.

PARAMETER	DESIGN REQUIREMENT
Input voltages (V_{IN1} and V_{IN2})	1.8 V, \pm 3%, provided by the dc-dc converter switching at 750 kHz
Maximum ambient operating temperature	85°C
Output voltages (V _{OUT1} and V _{OUT2})	1.2 V, ±1%, output voltages are isolated
Output currents (I _{OUT2} and I _{OUT2})	400 mA (maximum), 10 mA (minimum)
Channel-to-channel isolation	Isolation greater than 50 dB at 100 kHz
RMS noise	$< 5 \mu V_{RMS}$, bandwidth = 10 Hz to 100 kHz
PSRR at 750 kHz	> 40 dB
Startup time	< 5 ms

表 10. Design Parameters

8.2.2 Detailed Design Procedure

The output voltages can be set to 1.2 V by selecting the correct values for R_{1x} and R_{2x} ; see $\Delta \pm 1$.

Input and output capacitors are selected in accordance with the *External Component Selection* section. Ceramic capacitances of 10 µF for both inputs and outputs are selected.

To minimize noise, a feed-forward capacitance (C_{FFx}) of 10 nF is selected.

Channel-to-channel isolation depends greatly on the layout of the design. To minimize crosstalk between the outputs, keep the output capacitor grounds on separate sides of the design. See the *Layout* section for an example of how to layout the TPS7A87 to achieve best PSRR, channel-to-channel isolation, and noise.



8.2.3 Application Curves



9 Power Supply Recommendations

Both inputs of the TPS7A87 are designed to operate from an input voltage range between 1.4 V and 6.5 V. The input voltage range must provide adequate headroom in order for the device to have a regulated output. This input supply must be well regulated. If the input supply is noisy or has a high output impedance, additional input capacitors with low ESR can help improve the output noise performance.



10 Layout

10.1 Layout Guidelines

General guidelines for linear regulator designs are to place all circuit components on the same side of the circuit board and as near as practical to the respective LDO pin connections. Place ground return connections to the input and output capacitor, and to the LDO ground pin as close to each other as possible, connected by a wide, component-side, copper surface. The use of vias and long traces to create LDO circuit connections is strongly discouraged and negatively affects system performance.

10.1.1 Board Layout

To maximize the performance of the device, following the layout example illustrated in \mathbb{E} 65 is recommended. This layout isolates the analog ground (AGND) from the noisy power ground. Components that must be connected to the quiet analog ground are the noise-reduction capacitors ($C_{NR/SSx}$) and the lower feedback resistors (R_{2x}). These components must have a separate connection back to the thermal pad of the device. To minimize crosstalk between the two outputs, the output capacitor grounds are positioned on opposite sides of the layout and only connect back to the device at opposite sides of the thermal pad. Connecting the GND pins directly to the thermal pad and not to any external plane is recommended.

To maximize the output voltage accuracy, the connection from each output voltage back to the top output divider resistors (R_{1x}) must be made as close as possible to the load. This method of connecting the feedback trace eliminates the voltage drop from the device output to the load.

To improve thermal performance, a 3×3 thermal via array must connect the thermal pad to internal ground planes. A larger area for the internal ground planes improves the thermal performance and lowers the operating temperature of the device.



10.2 Layout Example





TPS7A87 ZHCSF74A – MARCH 2016 – REVISED JULY 2016 TEXAS INSTRUMENTS

www.ti.com.cn

11 器件和文档支持

- 11.1 器件支持
- 11.1.1 开发支持

11.1.1.1 评估模块

评估模块 (EVM) 可与 TPS7A87 配套使用,帮助评估初始电路性能。有关此固定装置的相关摘要信息,请参见表 11。

表 11. 设计套件与评估模块⁽¹⁾

名称	部件号
TPS7A88 评估模块	《TPS7A88EVM 用户指南》

(1) 欲获得最新的封装和订货信息,请参阅本文档末尾的封装选项附录,或者访问 www.ti.com 查看器件产品文件夹。

在德州仪器 (TI) 网站 (www.ti.com) 上,可通过 TPS7A87 产品文件夹获取 EVM。

11.1.1.2 SPICE 模型

分析模拟电路和系统的性能时,使用 SPICE 模型对电路性能进行计算机仿真非常有用。您可以从 TPS7A87 产品 文件夹中的仿真模型下获取 TPS7A87 的 SPICE 模型。

11.1.2 器件命名规则

表 12. 订购信息⁽¹⁾

产品	说明
TPS7A87 XXYYYZ	 XX 表示输出电压。01 为可调输出版本。 YYY 为封装标识符。 Z 为封装数量。

(1) 欲获得最新的封装和订货信息,请参阅本文档末尾的封装选项附录,或者访问 www.ti.com 查看器件产品文件夹。

11.2 文档支持

11.2.1 相关文档

相关文档如下:

- 数据表《TPS37xx 双通道、低功耗、高精度电压检测器》(文献编号: SBVS250)
- 用户指南《TPS7A88 评估模块》(文献编号: SBVU027)
- 应用报告《使用前馈电容器和低压降稳压器的优缺点》(文献编号: SBVA042)
- 白皮书《如何测量 LDO 噪声》(文献编号: SLYY076)

11.3 接收文档更新通知

如需接收文档更新通知,请访问 www.ti.com.cn 网站上的器件产品文件夹。点击右上角的提醒我 (Alert me) 注册 后,即可每周定期收到已更改的产品信息。有关更改的详细信息,请查阅已修订文档中包含的修订历史记录。



11.4 社区资源

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E[™] Online Community *TI's Engineer-to-Engineer (E2E) Community.* Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support TI's Design Support Quickly find helpful E2E forums along with design support tools and contact information for technical support.

11.5 商标

E2E is a trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

11.6 静电放电警告



ESD 可能会损坏该集成电路。德州仪器 (TI) 建议通过适当的预防措施处理所有集成电路。如果不遵守正确的处理措施和安装程序,可能会损坏集成电路。

ESD 的损坏小至导致微小的性能降级,大至整个器件故障。精密的集成电路可能更容易受到损坏,这是因为非常细微的参数更改都可能会导致器件与其发布的规格不相符。

11.7 Glossary

SLYZ022 — TI Glossary.

This glossary lists and explains terms, acronyms, and definitions.

12 机械、封装和可订购信息

以下页中包括机械、封装和可订购信息。这些信息是针对指定器件可提供的最新数据。这些数据会在无通知且不对 本文档进行修订的情况下发生改变。欲获得该数据表的浏览器版本,请查阅左侧的导航栏。

重要声明

德州仪器(TI)及其下属子公司有权根据 JESD46 最新标准,对所提供的产品和服务进行更正、修改、增强、改进或其它更改,并有权根据 JESD48 最新标准中止提供任何产品和服务。客户在下订单前应获取最新的相关信息,并验证这些信息是否完整且是最新的。所有产品的销售 都遵循在订单确认时所提供的TI 销售条款与条件。

TI保证其所销售的组件的性能符合产品销售时 TI 半导体产品销售条件与条款的适用规范。仅在 TI 保证的范围内,且 TI 认为有必要时才会使用测试或其它质量控制技术。除非适用法律做出了硬性规定,否则没有必要对每种组件的所有参数进行测试。

TI 对应用帮助或客户产品设计不承担任何义务。客户应对其使用 TI 组件的产品和应用自行负责。为尽量减小与客户产品和应 用相关的风险,客户应提供充分的设计与操作安全措施。

TI不对任何 TI 专利权、版权、屏蔽作品权或其它与使用了 TI 组件或服务的组合设备、机器或流程相关的 TI 知识产权中授予 的直接或隐含权限作出任何保证或解释。TI 所发布的与第三方产品或服务有关的信息,不能构成从 TI 获得使用这些产品或服 务的许可、授权、或认可。使用此类信息可能需要获得第三方的专利权或其它知识产权方面的许可,或是 TI 的专利权或其它 知识产权方面的许可。

对于 TI 的产品手册或数据表中 TI 信息的重要部分,仅在没有对内容进行任何篡改且带有相关授权、条件、限制和声明的情况 下才允许进行 复制。TI 对此类篡改过的文件不承担任何责任或义务。复制第三方的信息可能需要服从额外的限制条件。

在转售 TI 组件或服务时,如果对该组件或服务参数的陈述与 TI 标明的参数相比存在差异或虚假成分,则会失去相关 TI 组件 或服务的所有明 示或暗示授权,且这是不正当的、欺诈性商业行为。TI 对任何此类虚假陈述均不承担任何责任或义务。

客户认可并同意,尽管任何应用相关信息或支持仍可能由 TI 提供,但他们将独力负责满足与其产品及在其应用中使用 TI 产品 相关的所有法律、法规和安全相关要求。客户声明并同意,他们具备制定与实施安全措施所需的全部专业技术和知识,可预见 故障的危险后果、监测故障及其后果、降低有可能造成人身伤害的故障的发生机率并采取适当的补救措施。客户将全额赔偿因 在此类安全关键应用中使用任何 TI 组件而对 TI 及其代理造成的任何损失。

在某些场合中,为了推进安全相关应用有可能对 TI 组件进行特别的促销。TI 的目标是利用此类组件帮助客户设计和创立其特 有的可满足适用的功能安全性标准和要求的终端产品解决方案。尽管如此,此类组件仍然服从这些条款。

TI 组件未获得用于 FDA Class III(或类似的生命攸关医疗设备)的授权许可,除非各方授权官员已经达成了专门管控此类使 用的特别协议。

只有那些 TI 特别注明属于军用等级或"增强型塑料"的 TI 组件才是设计或专门用于军事/航空应用或环境的。购买者认可并同 意,对并非指定面向军事或航空航天用途的 TI 组件进行军事或航空航天方面的应用,其风险由客户单独承担,并且由客户独 力负责满足与此类使用相关的所有法律和法规要求。

TI 己明确指定符合 ISO/TS16949 要求的产品,这些产品主要用于汽车。在任何情况下,因使用非指定产品而无法达到 ISO/TS16949 要求,TI不承担任何责任。

	产品		应用
数字音频	www.ti.com.cn/audio	通信与电信	www.ti.com.cn/telecom
放大器和线性器件	www.ti.com.cn/amplifiers	计算机及周边	www.ti.com.cn/computer
数据转换器	www.ti.com.cn/dataconverters	消费电子	www.ti.com/consumer-apps
DLP® 产品	www.dlp.com	能源	www.ti.com/energy
DSP - 数字信号处理器	www.ti.com.cn/dsp	工业应用	www.ti.com.cn/industrial
时钟和计时器	www.ti.com.cn/clockandtimers	医疗电子	www.ti.com.cn/medical
接口	www.ti.com.cn/interface	安防应用	www.ti.com.cn/security
逻辑	www.ti.com.cn/logic	汽车电子	www.ti.com.cn/automotive
电源管理	www.ti.com.cn/power	视频和影像	www.ti.com.cn/video
微控制器 (MCU)	www.ti.com.cn/microcontrollers		
RFID 系统	www.ti.com.cn/rfidsys		
OMAP应用处理器	www.ti.com/omap		
无线连通性	www.ti.com.cn/wirelessconnectivity	德州仪器在线技术支持社区	www.deyisupport.com

邮寄地址: 上海市浦东新区世纪大道1568 号,中建大厦32 楼邮政编码: 200122 Copyright © 2016, 德州仪器半导体技术(上海)有限公司



10-Dec-2020

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
TPS7A8701RTJR	ACTIVE	QFN	RTJ	20	3000	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	TPS7A87	Samples
TPS7A8701RTJT	ACTIVE	QFN	RTJ	20	250	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	TPS7A87	Samples

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

⁽²⁾ RoHS: TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".

RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.

Green: TI defines "Green" to mean the content of Chlorine (CI) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <= 1000ppm threshold. Antimony trioxide based flame retardants must also meet the <= 1000ppm threshold requirement.

⁽³⁾ MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

⁽⁴⁾ There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

⁽⁵⁾ Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

⁽⁶⁾ Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer:The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



www.ti.com

PACKAGE OPTION ADDENDUM

10-Dec-2020

PACKAGE MATERIALS INFORMATION

www.ti.com

Texas Instruments

TAPE AND REEL INFORMATION





QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal												
Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPS7A8701RTJR	QFN	RTJ	20	3000	330.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2
TPS7A8701RTJT	QFN	RTJ	20	250	180.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2

TEXAS INSTRUMENTS

www.ti.com

PACKAGE MATERIALS INFORMATION

29-Jul-2016



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPS7A8701RTJR	QFN	RTJ	20	3000	367.0	367.0	35.0
TPS7A8701RTJT	QFN	RTJ	20	250	210.0	185.0	35.0

GENERIC PACKAGE VIEW

WQFN - 0.8 mm max height

PLASTIC QUAD FLATPACK - NO LEAD

This image is a representation of the package family, actual package may vary. Refer to the product data sheet for package details.





RTJ 20

4 x 4, 0.5 mm pitch

DATA BOOK PACKAGE OUTLINE

LEADFRAME EXAMPLE 4222370

DRAFTSMA	^{N:} H. DENG	DATE:	09/12/2016				DIMENSIONS IN I	MILLIM	IETERS
DESIGNER:	H. DENG	DATE:	09/12/2016			🦊 Texas Inst	RUMENTS	CO	
CHECKER:		DATE:				SEMICONDUCTOR	OPERATIONS	(1295
	V. PAKU & T. LEQUANG		09/12/2016						
ENGINEER:		DATE:						1	
	T. TANG		09/12/2016			ePOD, RIJUU		Ν,	
APPROVED		DATE:							
-	E. REY & D. CHIN		10/06/2016			20 PIN, 0.5 I			
RELEASED:		DATE:				•			
_	WDM		10/24/2016		-			_	-
			10/2 //2010	SCALE	SIZE			REV	PAGE
TEMPLATE	INFU:	DATE:		150	۸ I	I <u>42101</u> 2	25		1
	EDGE# 4218519		04/07/2016	10X	A	421312	_0		I OF D

RTJ0020D

PACKAGE OUTLINE

WQFN - 0.8 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.



RTJ0020D

EXAMPLE BOARD LAYOUT

WQFN - 0.8 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES: (continued)

- 4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).
- 5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.



RTJ0020D

EXAMPLE STENCIL DESIGN

WQFN - 0.8 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations..



REVISIONS							
REV	DESCRIPTION	ECR	DATE	ENGINEER / DRAFTSMAN			
А	RELEASE NEW DRAWING	2160736	10/24/2016	T. TANG / H. DENG			

SCALE	SIZE	
NTS	Α	

重要声明和免责声明

TI 提供技术和可靠性数据(包括数据表)、设计资源(包括参考设计)、应用或其他设计建议、网络工具、安全信息和其他资源,不保证没 有瑕疵且不做出任何明示或暗示的担保,包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任:(1) 针对您的应用选择合适的 TI 产品,(2) 设计、验 证并测试您的应用,(3) 确保您的应用满足相应标准以及任何其他安全、安保或其他要求。这些资源如有变更,恕不另行通知。TI 授权您仅可 将这些资源用于研发本资源所述的 TI 产品的应用。严禁对这些资源进行其他复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知 识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索赔、损害、成本、损失和债务,TI 对此概不负责。

TI 提供的产品受 TI 的销售条款 (https:www.ti.com.cn/zh-cn/legal/termsofsale.html) 或 ti.com.cn 上其他适用条款/TI 产品随附的其他适用条款 的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

> 邮寄地址:上海市浦东新区世纪大道 1568 号中建大厦 32 楼,邮政编码:200122 Copyright © 2021 德州仪器半导体技术(上海)有限公司